
Mobile Multimedia Terminal For DVB-T and Large and Small Cell Communication

U.S. Patent Application of:

Janne Aaltonen,	Inventor
Ari Ikonen,	Inventor
Pekka Talmola,	Inventor

<u>Nokia Mobile Phones, Ltd.,</u>	Assignee
-----------------------------------	----------

Attorney's Docket No.: NC-28066
ALLEN SCOTT LINEBERRY, PROV. REG. PAT. ATTY.

Attorney Work Product – Privileged and Confidential

Mobile Multimedia Terminal for DVB-T

And

Large and Small Cell Communication

Field of the Invention

This invention relates to multimedia terminals and, more particularly, to interactive multimedia terminals using DVB in a mobile environment.

Background of the Invention

The explosion of wireless data communication has been fueled by advances in semiconductor technology and software. These advances have allowed audio and data signals to be transmitted over digital networks.

Digital and mixed signal systems offer many advantages over old-fashioned analog systems. One important advantage is the ability of digital systems to transmit and receive more information at higher rates. Whereas analog systems are limited to transmitting audio and video at a rate of 64 Kbps, digital systems can compress such transmissions to transmit eight times as much information at the same rate. Moreover, faster processors have allowed digital systems to transmit bits at ever increasing rates. By taking advantage of the compression routines and faster processors to transmit information more accurately and at higher rates, significant savings have been realized in both switching capacity and ongoing line costs.

Additional advantages have been realized through the use of multiple access techniques such as Time Division Multiple Access ("TDMA") and Code Division Multiple Access ("CDMA"). These techniques allow for multiple users to access a single bandwidth. They also allow for audio and data signals

transmitted by a single user to be intermingled. These techniques make better use of scarce airwave space.

5 A recent development in the wireless information revolution has been the transmission of digital video signals over the airwaves, for example, using DVB-T. A similar development is occurring in the RF band, as efforts are being made to add video capability to cellular telephones, fax machines and computers. Before quality video capability can be added to these machines, however, a problem arising from bandwidth limitation must be overcome. Because these machines operate on frequencies between 900 and 1900 Mhz, the bandwidth is not wide enough to transmit the enormous amount of video and audio information that is required for quality motion pictures.

10
15
20
25
30
35
40
45
50
55
60
65
70
75
80
85
90
95
100
105
110
115
120
125
130
135
140
145
150
155
160
165
170
175
180
185
190
195
200
205
210
215
220
225
230
235
240
245
250
255
260
265
270
275
280
285
290
295
300
305
310
315
320
325
330
335
340
345
350
355
360
365
370
375
380
385
390
395
400
405
410
415
420
425
430
435
440
445
450
455
460
465
470
475
480
485
490
495
500
505
510
515
520
525
530
535
540
545
550
555
560
565
570
575
580
585
590
595
600
605
610
615
620
625
630
635
640
645
650
655
660
665
670
675
680
685
690
695
700
705
710
715
720
725
730
735
740
745
750
755
760
765
770
775
780
785
790
795
800
805
810
815
820
825
830
835
840
845
850
855
860
865
870
875
880
885
890
895
900
905
910
915
920
925
930
935
940
945
950
955
960
965
970
975
980
985
990
995
1000
1005
1010
1015
1020
1025
1030
1035
1040
1045
1050
1055
1060
1065
1070
1075
1080
1085
1090
1095
1100
1105
1110
1115
1120
1125
1130
1135
1140
1145
1150
1155
1160
1165
1170
1175
1180
1185
1190
1195
1200
1205
1210
1215
1220
1225
1230
1235
1240
1245
1250
1255
1260
1265
1270
1275
1280
1285
1290
1295
1300
1305
1310
1315
1320
1325
1330
1335
1340
1345
1350
1355
1360
1365
1370
1375
1380
1385
1390
1395
1400
1405
1410
1415
1420
1425
1430
1435
1440
1445
1450
1455
1460
1465
1470
1475
1480
1485
1490
1495
1500
1505
1510
1515
1520
1525
1530
1535
1540
1545
1550
1555
1560
1565
1570
1575
1580
1585
1590
1595
1600
1605
1610
1615
1620
1625
1630
1635
1640
1645
1650
1655
1660
1665
1670
1675
1680
1685
1690
1695
1700
1705
1710
1715
1720
1725
1730
1735
1740
1745
1750
1755
1760
1765
1770
1775
1780
1785
1790
1795
1800
1805
1810
1815
1820
1825
1830
1835
1840
1845
1850
1855
1860
1865
1870
1875
1880
1885
1890
1895
1900
1905
1910
1915
1920
1925
1930
1935
1940
1945
1950
1955
1960
1965
1970
1975
1980
1985
1990
1995
2000
2005
2010
2015
2020
2025
2030
2035
2040
2045
2050
2055
2060
2065
2070
2075
2080
2085
2090
2095
2100
2105
2110
2115
2120
2125
2130
2135
2140
2145
2150
2155
2160
2165
2170
2175
2180
2185
2190
2195
2200
2205
2210
2215
2220
2225
2230
2235
2240
2245
2250
2255
2260
2265
2270
2275
2280
2285
2290
2295
2300
2305
2310
2315
2320
2325
2330
2335
2340
2345
2350
2355
2360
2365
2370
2375
2380
2385
2390
2395
2400
2405
2410
2415
2420
2425
2430
2435
2440
2445
2450
2455
2460
2465
2470
2475
2480
2485
2490
2495
2500
2505
2510
2515
2520
2525
2530
2535
2540
2545
2550
2555
2560
2565
2570
2575
2580
2585
2590
2595
2600
2605
2610
2615
2620
2625
2630
2635
2640
2645
2650
2655
2660
2665
2670
2675
2680
2685
2690
2695
2700
2705
2710
2715
2720
2725
2730
2735
2740
2745
2750
2755
2760
2765
2770
2775
2780
2785
2790
2795
2800
2805
2810
2815
2820
2825
2830
2835
2840
2845
2850
2855
2860
2865
2870
2875
2880
2885
2890
2895
2900
2905
2910
2915
2920
2925
2930
2935
2940
2945
2950
2955
2960
2965
2970
2975
2980
2985
2990
2995
3000
3005
3010
3015
3020
3025
3030
3035
3040
3045
3050
3055
3060
3065
3070
3075
3080
3085
3090
3095
3100
3105
3110
3115
3120
3125
3130
3135
3140
3145
3150
3155
3160
3165
3170
3175
3180
3185
3190
3195
3200
3205
3210
3215
3220
3225
3230
3235
3240
3245
3250
3255
3260
3265
3270
3275
3280
3285
3290
3295
3300
3305
3310
3315
3320
3325
3330
3335
3340
3345
3350
3355
3360
3365
3370
3375
3380
3385
3390
3395
3400
3405
3410
3415
3420
3425
3430
3435
3440
3445
3450
3455
3460
3465
3470
3475
3480
3485
3490
3495
3500
3505
3510
3515
3520
3525
3530
3535
3540
3545
3550
3555
3560
3565
3570
3575
3580
3585
3590
3595
3600
3605
3610
3615
3620
3625
3630
3635
3640
3645
3650
3655
3660
3665
3670
3675
3680
3685
3690
3695
3700
3705
3710
3715
3720
3725
3730
3735
3740
3745
3750
3755
3760
3765
3770
3775
3780
3785
3790
3795
3800
3805
3810
3815
3820
3825
3830
3835
3840
3845
3850
3855
3860
3865
3870
3875
3880
3885
3890
3895
3900
3905
3910
3915
3920
3925
3930
3935
3940
3945
3950
3955
3960
3965
3970
3975
3980
3985
3990
3995
4000
4005
4010
4015
4020
4025
4030
4035
4040
4045
4050
4055
4060
4065
4070
4075
4080
4085
4090
4095
4100
4105
4110
4115
4120
4125
4130
4135
4140
4145
4150
4155
4160
4165
4170
4175
4180
4185
4190
4195
4200
4205
4210
4215
4220
4225
4230
4235
4240
4245
4250
4255
4260
4265
4270
4275
4280
4285
4290
4295
4300
4305
4310
4315
4320
4325
4330
4335
4340
4345
4350
4355
4360
4365
4370
4375
4380
4385
4390
4395
4400
4405
4410
4415
4420
4425
4430
4435
4440
4445
4450
4455
4460
4465
4470
4475
4480
4485
4490
4495
4500
4505
4510
4515
4520
4525
4530
4535
4540
4545
4550
4555
4560
4565
4570
4575
4580
4585
4590
4595
4600
4605
4610
4615
4620
4625
4630
4635
4640
4645
4650
4655
4660
4665
4670
4675
4680
4685
4690
4695
4700
4705
4710
4715
4720
4725
4730
4735
4740
4745
4750
4755
4760
4765
4770
4775
4780
4785
4790
4795
4800
4805
4810
4815
4820
4825
4830
4835
4840
4845
4850
4855
4860
4865
4870
4875
4880
4885
4890
4895
4900
4905
4910
4915
4920
4925
4930
4935
4940
4945
4950
4955
4960
4965
4970
4975
4980
4985
4990
4995
5000
5005
5010
5015
5020
5025
5030
5035
5040
5045
5050
5055
5060
5065
5070
5075
5080
5085
5090
5095
5100
5105
5110
5115
5120
5125
5130
5135
5140
5145
5150
5155
5160
5165
5170
5175
5180
5185
5190
5195
5200
5205
5210
5215
5220
5225
5230
5235
5240
5245
5250
5255
5260
5265
5270
5275
5280
5285
5290
5295
5300
5305
5310
5315
5320
5325
5330
5335
5340
5345
5350
5355
5360
5365
5370
5375
5380
5385
5390
5395
5400
5405
5410
5415
5420
5425
5430
5435
5440
5445
5450
5455
5460
5465
5470
5475
5480
5485
5490
5495
5500
5505
5510
5515
5520
5525
5530
5535
5540
5545
5550
5555
5560
5565
5570
5575
5580
5585
5590
5595
5600
5605
5610
5615
5620
5625
5630
5635
5640
5645
5650
5655
5660
5665
5670
5675
5680
5685
5690
5695
5700
5705
5710
5715
5720
5725
5730
5735
5740
5745
5750
5755
5760
5765
5770
5775
5780
5785
5790
5795
5800
5805
5810
5815
5820
5825
5830
5835
5840
5845
5850
5855
5860
5865
5870
5875
5880
5885
5890
5895
5900
5905
5910
5915
5920
5925
5930
5935
5940
5945
5950
5955
5960
5965
5970
5975
5980
5985
5990
5995
6000
6005
6010
6015
6020
6025
6030
6035
6040
6045
6050
6055
6060
6065
6070
6075
6080
6085
6090
6095
6100
6105
6110
6115
6120
6125
6130
6135
6140
6145
6150
6155
6160
6165
6170
6175
6180
6185
6190
6195
6200
6205
6210
6215
6220
6225
6230
6235
6240
6245
6250
6255
6260
6265
6270
6275
6280
6285
6290
6295
6300
6305
6310
6315
6320
6325
6330
6335
6340
6345
6350
6355
6360
6365
6370
6375
6380
6385
6390
6395
6400
6405
6410
6415
6420
6425
6430
6435
6440
6445
6450
6455
6460
6465
6470
6475
6480
6485
6490
6495
6500
6505
6510
6515
6520
6525
6530
6535
6540
6545
6550
6555
6560
6565
6570
6575
6580
6585
6590
6595
6600
6605
6610
6615
6620
6625
6630
6635
6640
6645
6650
6655
6660
6665
6670
6675
6680
6685
6690
6695
6700
6705
6710
6715
6720
6725
6730
6735
6740
6745
6750
6755
6760
6765
6770
6775
6780
6785
6790
6795
6800
6805
6810
6815
6820
6825
6830
6835
6840
6845
6850
6855
6860
6865
6870
6875
6880
6885
6890
6895
6900
6905
6910
6915
6920
6925
6930
6935
6940
6945
6950
6955
6960
6965
6970
6975
6980
6985
6990
6995
7000
7005
7010
7015
7020
7025
7030
7035
7040
7045
7050
7055
7060
7065
7070
7075
7080
7085
7090
7095
7100
7105
7110
7115
7120
7125
7130
7135
7140
7145
7150
7155
7160
7165
7170
7175
7180
7185
7190
7195
7200
7205
7210
7215
7220
7225
7230
7235
7240
7245
7250
7255
7260
7265
7270
7275
7280
7285
7290
7295
7300
7305
7310
7315
7320
7325
7330
7335
7340
7345
7350
7355
7360
7365
7370
7375
7380
7385
7390
7395
7400
7405
7410
7415
7420
7425
7430
7435
7440
7445
7450
7455
7460
7465
7470
7475
7480
7485
7490
7495
7500
7505
7510
7515
7520
7525
7530
7535
7540
7545
7550
7555
7560
7565
7570
7575
7580
7585
7590
7595
7600
7605
7610
7615
7620
7625
7630
7635
7640
7645
7650
7655
7660
7665
7670
7675
7680
7685
7690
7695
7700
7705
7710
7715
7720
7725
7730
7735
7740
7745
7750
7755
7760
7765
7770
7775
7780
7785
7790
7795
7800
7805
7810
7815
7820
7825
7830
7835
7840
7845
7850
7855
7860
7865
7870
7875
7880
7885
7890
7895
7900
7905
7910
7915
7920
7925
7930
7935
7940
7945
7950
7955
7960
7965
7970
7975
7980
7985
7990
7995
8000
8005
8010
8015
8020
8025
8030
8035
8040
8045
8050
8055
8060
8065
8070
8075
8080
8085
8090
8095
8100
8105
8110
8115
8120
8125
8130
8135
8140
8145
8150
8155
8160
8165
8170
8175
8180
8185
8190
8195
8200
8205
8210
8215
8220
8225
8230
8235
8240
8245
8250
8255
8260
8265
8270
8275
8280
8285
8290
8295
8300
8305
8310
8315
8320
8325
8330
8335
8340
8345
8350
8355
8360
8365
8370
8375
8380
8385
8390
8395
8400
8405
8410
8415
8420
8425
8430
8435
8440
8445
8450
8455
8460
8465
8470
8475
8480
8485
8490
8495
8500
8505
8510
8515
8520
8525
8530
8535
8540
8545
8550
8555
8560
8565
8570
8575
8580
8585
8590
8595
8600
8605
8610
8615
8620
8625
8630
8635
8640
8645
8650
8655
8660
8665
8670
8675
8680
8685
8690
8695
8700
8705
8710
8715
8720
8725
8730
8735
8740
8745
8750
8755
8760
8765
8770
8775
8780
8785
8790
8795
8800
8805
8810
8815
8820
8825
8830
8835
8840
8845
8850
8855
8860
8865
8870
8875
8880
8885
8890
8895
8900
8905
8910
8915
8920
8925
8930
8935
8940
8945
8950
8955
8960
8965
8970
8975
8980
8985
8990
8995
9000
9005
9010
9015
9020
9025
9030
9035
9040
9045
9050
9055
9060
9065
9070
9075
9080
9085
9090
9095
9100
9105
9110
9115
9120
9125
9130
9135
9140
9145
9150
9155
9160
9165
9170
9175
9180
9185
9190
9195
9200
9205
9210
9215
9220
9225
9230
9235
9240
9245
9250
9255
9260
9265
9270
9275
9280
9285
9290
9295
9300
9305
9310
9315
9320
9325
9330
9335
9340
9345
9350
9355
9360
9365
9370
9375
9380
9385
9390
9395
9400
9405
9410
9415
9420
9425
9430
9435
9440
9445
9450
9455
9460
9465
9470
9475
9480
9485
9490
9495
9500
9505
9510
9515
9520
9525
9530
9535
9540
9545
9550
9555
9560
9565
9570
9575
9580
9585
9590
9595
9600
9605
9610
9615
9620
9625
9630
9635
9640
9645
9650
9655
9660
9665
9670
9675
9680
9685
9690
9695
9700
9705
9710
9715
9720
9725
9730
9735
9740
9745
9750
9755
9760
9765
9770
9775
9780
9785
9790
9795
9800
9805
9810
9815
9820
9825
9830
9835
9840
9845
9850
9855
9860
9865
9870
9875
9880
9885
9890
9895
9900
9905
9910
9915
9920
9925
9930
9935
9940
9945
9950
9955
9960
9965
9970
9975
9980
9985
9990
9995
10000
10005
10010
10015
10020
10025
10030
10035
10040
10045
10050
10055
10060
10065
10070
10075
10080
10085
10090
10095
10100
10105
10110
10115
10120
10125
10130
10135
10140
10145
10150
10155
10160
10165
10170
10175
10180
10185
10190
10195
10200
10205
10210
10215
10220
10225
10230
10235
10240
10245
10250
10255
10260

uplink her report to a programming center. The material is digitally received, decoded, and compiled with live program feeds in a studio. The broadcast is then sent digitally around the world to professional receivers. Finally, the broadcast is converted to an analog signal and sent to the end viewer.

5

An intelligent TV can receive communication services by connecting a TV to a value added network (VAN). The intelligent TV includes an information signal processing unit for receiving information communication data (hereinafter, "information data") when the intelligent TV is connected to the VAN, and for generating information RGB signals, and switching control signals in order to display the information data on a screen. The intelligent TV selects and displays on the screen one of the information data signals processed in the information signal processing unit and a TV RGB signal processed in a TV signal processing unit, in accordance with the switching control signal output from the information signal processing unit. Intelligent TV makes it possible to view, through a TV screen, several communication services, such as stock quotes, news services, weather reports, and TV program lists, being transmitted through the VANs. Therefore, it has an advantage that persons who are not familiar with the usage of a computer can easily receive communication services.

20

Even though intelligent TV has the advantage of receiving communication services through the TV screen, it cannot display multiple signals at the same time. Information signals for displaying information data on a screen, a TV signal, a Picture-In-Picture (PIP) signal for enabling two screens to be viewed simultaneously, and a TV on-screen-display (OSD) signal must be displayed one at a time. Therefore, signals are displayed according to a predetermined priority. For example, an information signal is displayed

25

preferentially over a TV signal, a PIP signal is displayed preferentially over an information signal, and a TV OSD signal is displayed preferentially over a PIP signal.

Current information delivery services described above lack many features that would enhance their usability and desirability by the public. As mentioned, the intelligent TV lacks an ability to display multiple signals simultaneously. In addition, an online connection of two delivery services with one of the services being, for example, an interactive application, is not available. Current technologies are dependent on stationary receivers. Since multiple signals cannot be integrated by the integrated receiver/decoder (or IRD), information delivery is dependent on the location or site.

New display technologies provide the possibility to build low power and high quality portable display devices. These devices are based on large full color flat panel displays or on virtual (helmet mount) displays. The common denominator for these kinds of displays is that they are digital and matrix type displays. Introduction of DVB-T enables, for the first time in TV broadcast history, the possibility of truly mobile reception of TV. In addition to conventional TV services, DVB-T provides access to broadcast data services. Integration of DVB-T with digital display unit, such as the flat panel or helmet mount displays described above, makes it possible to build fully digital TV receiver with studio quality picture.

Figure 3 depicts a block diagram of the current multimedia architecture. Currently, the digital set-top-box (STB) **302** and digital TV display **304** are separate. Furthermore, the STB 302 communication link is only of a single type. For example, the STB communications link is a hard interface such as coax-cable or POTS. Therefore, the typical digital TV 304 connected to an STB 302 offers no portability or mobility.

Laptop and notebook computers are now equipped with the means to connect to networks using a mobile (or wireless) link. Such connections usually utilize a modem and digital wireless transceiver built on a single card, e.g., a PCMIA card. However, digital TV receivers have not been integrated into such devices. One reason for this lack of versatility is that digital TV receivers have high power consumption rates (relative to other laptop or notebook functions). Thus, the battery power of a laptop would be consumed rapidly. In addition, laptops, like STBs, are typically limited in their ability to communicate externally. For example, a serial port, parallel port and possibly a modem can be used to distribute information from a laptop. However, such devices do not switch between these links seamlessly. Further, such devices do not have the ability to take stock of their environment and dynamically switch to the most appropriate communication link.

Summary of the Invention

The disclosed embodiments provide a method and apparatus for providing an interactive mobile multimedia terminal. The mobile multimedia terminal (or MMT) allows for wideband data stream reception using a digital data broadcast receiver such as DVB-T. Interactivity is realized with built-in local or large cell size communications link. The local link could be WLAN or Bluetooth (a low-power RF transceiver). The large cell size communications link could be a mobile station link e.g., GSM, CDMA, TDMA, etc. A mobile station with a Bluetooth link can be used as an IP router or a portable base station for large cell size communication if no local connection point is found. The MMT integrates DVB-T reception, digital display, and communications links together to provide interactivity in a mobile environment. The MMT communications link with a mobile station enables it to act as an extended

display for the mobile station. The MMT can also act as a graphical interface for SMS messaging via the mobile station or manipulating other applications on the mobile station.

The disclosed embodiments can provide several advantages. For example, the MMT is a single device that can be used in a portable or mobile environment. The MMT is configured with different wireless links, enabling it to adapt seamlessly and dynamically to its communications environment by switching between different communications interfaces, protocols, or links. For another example, the MMT can be used to receive and display (or broadcast) different kind of data. Such data can include, for example, digital content *e.g.*, MP3 files, e-books, or newspapers, e-commerce data, or broadcast TV. For another example, the timing and synchronization manager can be used to save power by controlling the digital receiver of the MMT.

Brief Description of the Drawings

The disclosed inventions will be described with reference to the accompanying drawings, which show important sample embodiments of the invention and which are incorporated in the specification hereof by reference, wherein:

Figure 1 depicts the presently preferred embodiment of the mobile multimedia terminal;

Figure 2 depicts the presently preferred embodiment of a MMT and its corresponding communications environment;

Figure 3 depicts a block diagram of the current multimedia architecture; and

Figure 4 depicts a block diagram of a mobile station **400** that can act as an IP router or portable base station to the MMT 100.

Detailed Description of the Preferred Embodiments

The numerous innovative teachings of the present application will be described with particular reference to the presently preferred embodiment. However, it should be understood that this class of embodiments provides only a few examples of the many advantageous uses of the innovative teachings herein. In general, statements made in the specification of the present application do not necessarily delimit any of the various claimed inventions. Moreover, some statements may apply to some inventive features but not to others.

Figure 1 depicts the presently preferred embodiment of the mobile multimedia terminal (or MMT). The MMT provides an interactive, mobile environment. In the presently preferred embodiment, a DVB-T receiver **102** is controlled by a CPU **104**. The DVB-T receiver **102** is capable of receiving digital TV broadcasts according to the DVB-T standard. DVB-S (satellite) and DVB-C (cable) broadcasts are also standardized and may be used. The DVB-T standard specifies a broadband channel, preferably in the VHF frequency range, that carries a digital data stream. In addition to TV broadcasts, channels in the DVB-T spectrum can be used to transmit data intended for receipt by specific users. Such data is generally encrypted for privacy. In this manner, DVB-T (or DVB-S or DVB-C) can be used for data transmission which requires a wideband downstream channel (from the source to the requestor). In the presently preferred embodiment, the MMT **100** is the requestor.

A media decoder **106** is controlled by the CPU **104** and used to decode the received DVB-T broadcast. The DVB-T broadcast standard uses MPEG-2 encoding. Therefore, in the presently preferred embodiment, the media decoder **106** is an MPEG-2 decoder. However, other forms of streaming video can and do use alternate protocols to transmit digital data. The media decoder **106**

selected should be designed to match and decode the transmission protocol used by the digital data source.

5 A display interface **108** receives the decoded broadcast from the media decoder 106. The display interface 108 is designed to optimize the display of data to a user of the MMT 100. For example, the digital data received can be in the form of full motion video or it can be a graphic of some kind. The differing formats require differing modes to be optimally displayed. The display interface 108 acts as a video integrator. For example, the display interface can place a graphics overlay onto full motion video, manipulate the display of full motion video into a certain part of a display, or crop some video or graphics to show only their essential or moving parts on a display. The output of the display interface 108 drives a display **110** for the MMT 100.

10 In addition to processing a digital broadcast signal, the MMT 100 of the presently preferred embodiment is capable of transmitting information. Such information can include requests for information, data to be downloaded via digital broadcast, phone identification data, or regular voice and data communications over a mobile station (such as a mobile phone). In the presently preferred embodiment, the MMT 100 is equipped with a low-power radio frequency (LPRF) e.g., Bluetooth, transceiver **112**. A transceiver configured according to the Bluetooth standard is capable of short range (approximately 10 meters) radio communication to a local transceiver. The local transceiver can be connected to a LAN, PSTN, or a low or high power wireless network. In addition to a LPRF link, the MMT 100 of the presently preferred embodiment can be configured with a Wireless-LAN **114** or cellular transceiver **116**. The cellular transceiver can be, for example, a GSM, TDMA, CDMA, AMPS, or other standard or proprietary communications protocol. The CPU controller 104 of the MMT 100 is configured to select the mode of

communication between transceivers 112, 114, and 116 dynamically. The CPU 104 can select the appropriate communications link according to the current communications environment. For example, if a Bluetooth transceiver is detected, data can be exchanged using the Bluetooth transceiver 112 without the need for acquiring a channel on a cellular link. However, if voice data is to be transmitted, a cellular link would be desirable. Thus the CPU 104 would select the cellular transceiver 106 for transmission duties.

The LPRF link 112 of the MMT 100 can be used in conjunction with an external mobile station. The external mobile station can act as a portable (close range) base station. The external mobile station can also act as an IP router for web browsing and other network activities.

The DVB-T receiver 102 of the MMT 100 is activated or deactivated by the CPU 104. The DVB-T receiver 102 can be activated at user request. That is, when the user wishes to receive broadcast data or is expecting to receive broadcast data. The CPU 104 can also monitor the environment for service information and activate the DVB-T receiver 102 if conditions warrant it. For example, if services the user wishes to receive are detected, the CPU 104 can activate the DVB-T receiver 102. As another example, the CPU 104 can activate the DVB-T receiver 102 if and when it needs to, in order to impart important or timely data to the user, e.g., weather or news data.

In the presently preferred embodiment, the DVB-T receiver 102 is equipped with a timing element 118 enabling it to remain synchronous with the digital broadcast facility. This timer 118 makes it possible to switch on the receiver and pick up the selected data packets days after the last system synchronization. The timer 118 allows the CPU 104 to control activation of the DVB-T receiver 102 also enables power savings. For example, if video functionality is not currently in use, that is, digital broadcasts are not being or

do not need to be received, the DVB-T receiver 102 is switched off by the CPU 104. Such a situation can occur when, for example, the MMT is web browsing over a communications link 112, 114, or 116.

5 **Figure 2** depicts the presently preferred embodiment of a MMT 100 and its corresponding communications environment **200**. Media is provided by a service provider **202**. Media can include, for example, data services, decryption keys for smart cards, digital TV, digital audio, or other digital data. The media can be provided on the request by user or under a “broadcast” principle. In the presently preferred embodiment specific requests for data are handled via a mobile station **204** equipped with an LPRF transceiver. The requests are transmitted via an LPRF link from the MMT 100 to the mobile station 204. The mobile station 204 relays the request via a wireless operator **206**. The service provider 202 capable of providing the requested data receives the request from the wireless operator 206. The media content is routed from the service provider 202, via DVB-scrambling **210**, to a DVB Network operator **212**. The DVB Network operator 212 multiplexes the media content with free to air TV Services **214** and transports the data over a DVB broadcast channel **208**.

20 At the MMT 100, the DVB-T transmission is received by the DVB-T receiver 102. A front end receiver **216** in the DVB-T receiver 102 receives the transmission, acting as the over-the-air interface of the receiver 102. Data is transmitted to a descrambler **218** with a smart card **220**. The descrambler 218 is optional in the presently preferred embodiment. The decrypted/descrambled data is then forwarded to a demultiplexer **222**.

25 The front end 216, descrambler 218, smart card 220, and demultiplexer 222 consume a majority of the power used by the DVB receiver 102. Data for

the demultiplexer 222 is routed to the media decoder 106. Alternatively, the data can be routed to buffer or storage memory 224 or an optional memory card 226. Storing the data instead of decoding and displaying it is dependent on the set up and usage of the DVB-T receiver 102. For example, by storing data into memory, it is possible to display one data stream while receiving another. In the presently preferred embodiment, the timing and synchronization manager 118 controls the front end 216, descrambler 218, smart card 220, and demultiplexer 222. The timing and synchronization manager 118 activates these receiver components only when needed or upon user request. The CPU 104 of the MMT 100 controls all of the components of the MMT. The CPU 104 is responsible for reading the service information and determining the communication environment of the MMT 100. The CPU 104 is used to configure the timing and synchronization manager 118.

Content to be shown on the display 110 of the MMT 100 can originate either from CPU 104 via memory 224 or 226 or from media decoder 106. The display of the MMT 100 can be, for example, a flat panel TFT display or a virtual display such as a head mounted LCOS 3D display. Display data is processed by the display interface 108 of the MMT. This interface 108 performs the needed operations of scaling, zooming, frame rate conversions, filtering, in order to appropriately display the data on the display 110 of the MMT 100. The display interface 108 can be configured to optimally display data depending on its type and the type of display 110 to be utilized.

Digital content can also include audio signals. Such content can be presented through the audio output 230 of the MMT 100. The audio output 230 of the MMT can be, *e.g.*, speakers.

The MMT 100 can be configured to communicate in a variety of ways. For example, an LPRF link 112 can be used to communicate with a mobile

station acting as a portable base station or IP router. For another example, in a home gateway environment, the MMT 100 can act as a node in a Wireless LAN using a WLAN transceiver 114.

5 **Figure 4** depicts a block diagram of a mobile station **400** that can act as an IP router or portable base station to the MMT 100. The mobile station 400 includes, in this example:

10 A control head **402** containing an audio interface, i.e. a speaker **404** and microphone **406**. The control head 402 generally includes a display assembly **408** allowing a user to see dialed digits, stored information, messages, calling status information, including signal strength, etc. The control head generally includes a keypad **410**, or other user control device, allowing a user to dial numbers, answer incoming calls, enter stored information, and perform other mobile station functions. The control head also has a controller unit **434** that
15 interfaces with a logic control assembly **418** responsible, from the control unit perspective, for receiving commands from the keypad 410 or other control devices, and providing status information, alerts, and other information to the display assembly 408;

20 A transceiver unit **412** containing a transmitter unit **414**, a receiver unit **416**, and the logic control assembly 418. The transmitter unit 414 converts low-level audio signals from the microphone 406 to digital coding using a codec (a data coder/decoder) **420**. The digitally encoded audio is represented by modulated shifts, for example, in the frequency domain, using a shift key modulator/demodulator **422**. Other codes transmission utilized by the logic
25 control assembly 418, such as station parameters and control information, may also be encoded for transmission. The modulated signal is then amplified **424** and transmitted via an antenna assembly **426**;

The antenna assembly 426 contains a TR (transmitter/receiver) switch 436 to prevent simultaneous reception and transmission of a signal by the mobile station 400. The transceiver unit 412 is connected to the antenna assembly 426 through the TR switch 436. The antenna assembly contains at least one antenna 438;

The receiver unit 416 receives a transmitted signal via the antenna assembly 426. The signal is amplified 424 and demodulated 422. If the signal is an audio signal, it is decoded using the codec 420. The audio signal is then reproduced by the speaker 404. Other signals are handled by the logic control assembly 418 after demodulation 422; and

A logic control assembly 418 usually containing an application specific integrated circuit (or ASIC) combining many functions, such as a general purpose microprocessor, digital signal processor, and other functions, into one integrated circuit. The logic control assembly 418 coordinates the overall operation of the transmitter and receiver using control messages. The various disclosed embodiments make use of the logic control assembly to control scanning and evaluation of other base stations. Generally, the logic control assembly operates from a program that is stored in flash memory 428 of the mobile station. Flash memory 428 allows upgrading of operating software, software correction or addition of new features. Flash memory 428 is also used to hold user information such as speed dialing names and stored numbers.

In addition to flash memory 428, the mobile station will typically contain read only memory (ROM) 430 for storing information that should not change, such as startup procedures, and random access memory (RAM) 432 to hold temporary information such as channel number and system identifier.

In the presently preferred embodiment, the mobile station also includes an LPRF transceiver 112, *e.g.*, Bluetooth, for communication with the MMT 100.

5 **Modifications and Variations**

As will be recognized by those skilled in the art, the innovative concepts described in the present application can be modified and varied over a tremendous range of applications, and accordingly the scope of patented subject matter is not limited by any of the specific exemplary teachings given.

10 For example, the digital receiver is described as a DVB-T receiver. However, the digital data received could be in any of a variety of digital formats, frequencies, protocols, etc. The digital receiver used should be configured to receive the types of data expected. Moreover, the digital receiver could be configured to receive digital information in a variety of formats or
15 receive analog *e.g.*, NTSC or PAL, and digital broadcasts.

For another example, the presently preferred embodiment is described as having only one digital receiver. However, differing embodiments of the MMT may be configured with multiple digital receivers. The use of more than one digital receiver can serve to increase the robustness of the data received in
20 digital broadcast.

For another example, the presently preferred embodiment is described as operating over differing communications links, one at a time. However, it is possible that several of the communications links, *e.g.*, LPRF, WLAN, and/or a wireless mobile station link can be operated at once to send and receive
25 information to multiple places simultaneously.

For another example, while not stated explicitly in the presently preferred embodiment, it is possible to integrate a mobile station into the MMT. An

integrated MMT/mobile station would allow the MMT to function as its own IP router or portable base station.

For another example, digital broadcast of data is anticipated in the presently preferred embodiment. However, it is possible that third generation (3G) or greater cellular networks will have the capacity to deliver TV reception and broadband data transmission. The MMT can be equipped with a different or alternate receiver which is configured to receive such digital data.

5